

Hunter HDMI 2.0 1x16 Splitter 4K@60Hz

9152-HUS-HD1x16-4K60

User Manual



Product Introduction

Hunter 1x16 HDMI 2.0 Splitter uses a single HDMI source splitting the signals to multiple HDMI devices. It allows one HDMI device to be split easily to sixteen HDMI compatible monitors or projectors. The Splitter can also be placed at the end of a long HDMI cable to regenerate the HDMI signal. Resolution up to 3840X2160/60Hz.

Features

- Supports up to 4K2K resolution at 30Hz
- HDMI 1.4 compatibility
- Deep Color support: 8-bit, 10-bit, 12-bit
- Audio support for DTS-HD, Dolby TrueHD, DTS, Dolby AC3, DSD
- Maximum bandwidth of 340 MHz
- Baud rate up to 3.4 Gbps
- Transfer rate upto 6Gbps data rate for TMDS clock up to 600MHz
- Compact and lightweight design

When the resolution is 1080p and below, input up to 10 meters, output up to 15 meters.

When the resolution is 4K/30Hz, input up to 5 meters, output up to 10 meters.


- Support displaying single source, multi-output high-definition signal source from DVD player A / V receiver, set-top box
- DC 12V/3A power adapter

Specifacition



HDMI version	HDMI 2.0
HDMI resolution	H 3840*2160/60Hz
Support video color format	deep color 8/10/12bit
Support audio format	DTS-HD/Dolby-trueHD/DTS/Dolby-AC3/DSD
Max bandwidth	600MHz
Max transmission bandwidth	6Gbps
Input cable distance	(1080p resolution) ≤10m,(4K resolution)≤5m AWG26 HDMI standard cable
Output cable distance	(1080p resolution) ≤15m,(4K resolution)≤10m AWG26 HDMI standard cable
HDMI input	1
HDMI output	16
Max working current	1.15A
Power adapter format Input	AC (50HZ, 60HZ) 100V-240V; Output: DC12V/3A
Operating Temperature range	(-15 to +55°C)
Operating Humidity range	5 to 90%RH (No Condensation)
Dimension (L x W x H)	482x105x25 (mm)
Weight	1.54kg

EDID Settings



1	2	3	4	
X	0	0	0	Copy EDID from Output 1
X	0	0	1	EDID Mixed Output(1-8)
X	0	1	0	4k60,3840x2160, 60Hz, RGB, 8bit. 7.1Channel audio, 24-bit, 192Khz, DTS audio and Dolby Digital
X	0	1	1	4k30, 3840x2160, 30Hz, 4:4:4, 8bit. 2Channel, 24-bit, 48Khz
X	1	0	0	4k60, 3840x2160, 60Hz, 4:4:4, 8bit. 2Channel, 24-bit, 48Khz
X	1	0	1	1080p 3D 2ch, 1920x1080, 60Hz, 4:4:4, 8bit. 2Channel, 24-bit, 48Khz
X	1	1	0	1080p 2D 2ch, 1920x1080, 60Hz, 4:4:4, 8bit. 2Channel, 24-bit, 48Khz
X	1	1	1	1080p 2D 5.1ch, 1920x1080, 60Hz, 4:4:4, 8bit. 6Channel, 24-bit, 48Khz

Connection Diagram

1. Connect 1 HDMI cable from HDMI source devices into HDMI Splitter input.
2. Connect 16 HDMI cables from each displays (monitors or projectors) into the HDMI Splitter outputs.
3. Connect 12V/3A power adapter supply to the HDMI Splitter 1x16.



Teaching



TV Store



Market

Front



Back



Package Content



Hunter HDMI 2.0 1x16 Splitter



RS232

Warranty 1 Year



If your product does not work properly because of a defect in materials or workmanship, our Company (warrantor) will, for the length of the period indicated as 1 Years, which starts with the date of original purchase ("Limited Warranty period"), at its option either (a) repair your product with new or refurbished parts, or (b) replace it with a new or a refurbished product. The decision to repair or replace will be made by the warrantor.

During the "Labor" Limited Warranty period there will be no charge for labor.

During the "Parts" warranty period, there will be no charge for parts. You must mail-in your product during the warranty period. This Limited Warranty is extended only to the original purchaser and only covers product purchased as new. A purchase receipt or other proof of original purchase date is required for Limited Warranty service.