

# Hunter 1x4 HDMI Splitter

9250-HTV-SP4K10418G Hunter  
1X4 Splitter 4K

## USER MANUAL

[www.hunterindia.in](http://www.hunterindia.in)



## Product Introduction

Hunter 1x4 HDMI Splitter with HDCP 2.2 is an advanced solution for splitting a single HDMI input to four HDMI outputs. It provides high performance audio and video output through HDMI cables up to 4K2K@60Hz (YUV444) resolution and is capable of receiving and transmitting up to 18Gbps of bandwidth with no data loss. Supporting the latest features you can be assured of reliable and high quality HDMI distribution

[www.hunterindia.in](http://www.hunterindia.in)

## Features

- Supports EDID control Compliant with HDMI2.0, HDCP2.2
- Support 3D frame sequential video format up to 1080p@60
- Support high resolution VESA mode video format up to QSXGA@60Hz
- Supports LPCM 7.1CH, Dolby True HD, and DTS-HD Master Audio
- Support video format up to 4k2k@30Hz with 24bit RGB/YCBCR 4:4:4/YCBCR 4:2:2, and up to 4k2k@60Hz with 12bit YCBCR 4:4:4

## Specifacition



• Product Name	9250- Hunter 1x4 HDMI Splitter
• Input Port	1 × HDMI (Female type)
• Output Port	4 × HDMI (Female type)
• Output Resolution	480i ~1080p50/60, 4Kx2K@24/30, 4k2k@60Hz
• ESD Protection	Human Body Model: ± 8 KV (air-gap discharge) ± 4 KV (contact discharge)
• Video Bandwidth	600MHz/18Gbps
• Power Supply	5V/1A DC (US/EU standards, CE/FCC/UL certified)
• Material	Aluminum
• Operating Temperature	0 °C~40 °C/ 32 °F~104 °F
• Storage Temperature	-20 °C ~ 60 °C/-4 °F ~140 °F
• Relative Humidity	20~90 % RH (non-condensing)
• Power Consumption (Max)	5W

## Operation Controls & Functions



**Front Panel**

**POWER LED:**  
This LED illuminate when the device is connected with power supply

**1~4 LED:**  
This LED illuminate when the OUT1~OUT4 connected to the device

**IN LED:**  
This LED illuminate when the Source connected to the device

**ON/OFF button:**  
When the button is pressed, the device will be turned on/off

[www.hunterindia.in](http://www.hunterindia.in)



**Rear Panel**

**DC/5V:**  
Plug the 5V DC power supply into the unit and connected the adaptor to an AC outlet.

**HDMI IN:**  
Connect the input port to the HDMI or DVI output of your source device such as a DVD player or set-top box with an HDMI cable

**HDMI OUT 1~4:**  
Connect HDMI output 1~4 to an HDMI display for simultaneous HDMI distribution, or cascade the output to another transmitter to extend the operating distance.

11	Mixed EDID
00	Copy EDID from Output 4
10	Default 1080p output
01	Default 4KX2K output

## Packing Content

Hunter 1x4 HDMI Splitter

5V1A DC Power adapter

